



**Illuminance at a Distance at 25 Watts**

|         | Center Beam fc | Beam Width |         |
|---------|----------------|------------|---------|
| 10.0 ft | 13.2 fc        | 18.8 ft    | 19.6 ft |
| 15.0 ft | 5.9 fc         | 28.3 ft    | 29.4 ft |
| 20.0 ft | 3.3 fc         | 37.7 ft    | 39.2 ft |
| 25.0 ft | 2.1 fc         | 47.1 ft    | 48.9 ft |
| 30.0 ft | 1.5 fc         | 56.5 ft    | 59.2 ft |

■ Vert. Spread: 86.6°  
■ Horiz. Spread: 88.8°

### Specifications

|                               |                               |
|-------------------------------|-------------------------------|
| Item                          | - 36778A                      |
| Model                         | - LED WRAP 2FT 15/20/25W 3CCT |
| Bulb Type                     | - LED                         |
| Volts                         | - 120-347VAC 50/60Hz          |
| Dimmable                      | - Yes (0-10V)                 |
| Watts                         | - 15/20/25                    |
| Color Temp                    | - 35K/4K/5K                   |
| CRI                           | - 80                          |
| Lumen                         | - 1725/2300/2875              |
| Length                        | - 24" (609mm)                 |
| Width                         | - 7" (177mm)                  |
| Height                        | - 2.5" (64mm)                 |
| Life                          | - 50,000 Hours                |
| Location Rating               | - Suitable for dry locations  |
| Ambient Operating Temperature | - -22°F to 122°F              |
| Surge Protection              | - 2KV                         |

### Caution

- This fixture must be wired in accordance with the National Electrical Code and applicable local ordinance. Proper grounding is required to insure personal safety. Carefully observe grounding procedure under installation section.
- Make certain power is OFF before starting installation or attempting any maintenance. Risk of fire/electric shock. If not qualified, consult an electrician.
- Disconnect power at fuse or circuit breaker before installing or servicing
- RISK OF BURN--Disconnect power and allow fixture to cool before servicing.
- RISK OF PERSONAL INJURY--Fixture may become damaged and/or unstable if not installed properly. Tighten all fixture components to their recommended torque values.
- RISK OF FIRE--Fixture is rated for use in 120-347VAC 50/60Hz VAC protected circuit and 194°F rated supply wire.
- Suitable for dry locations only.

### Precaución

Este accesorio debe cablearse de acuerdo con el Código Eléctrico Nacional y la ordenanza local aplicable. Se requiere una conexión a tierra adecuada para garantizar la seguridad personal. Observe cuidadosamente el procedimiento de conexión a tierra en la sección de instalación.

Asegúrese de que la alimentación esté apagada antes de comenzar la instalación o intentar realizar cualquier tipo de mantenimiento. Riesgo de incendio / descarga eléctrica. Si no está calificado, consulte a un electricista.

Desconecte la energía en el fusible o disyuntor antes de instalación o mantenimiento

RIESGO DE QUEMADURAS: desconecte la alimentación y permita que el accesorio se enfríe antes de realizar el mantenimiento.

RIESGO DE LESIONES PERSONALES: el accesorio puede dañarse o inestarse si no se instala correctamente. Apriete todos los componentes del accesorio a sus valores de torque recomendados.

RIESGO DE INCENDIO: el accesorio está clasificado para su uso en 120-347VAC, circuito protegido 50-60 Hz y cable de suministro con clasificación de 194 ° F.

Apto solo para lugares secos.

