

Corn Cob Post Top

Specifications



Item - 34163A

Model - LED150CC/5K

Bulb Shape - Corn Cob

Bulb Type - LED

Beam Spread - 360 Degrees

Input Voltage - AC 100-277 (50 / 60 Hz)

Watts - 150W

Base Type - E39

Base Material - Nickel Plated Brass

Diameter - 4.875" (123mm)

Height - 13.125" (330mm)

Color Temp - 5000K

CRI - 80

Lumen - 18750

Operating Temp - -4F to 113F (-20C to 45C)

Dimmable - No

UL Rating - Suitable for Dry/Damp Location

Enclosed Rated - Yes

Burn Position - Universal

Life - 50,000 Hours

Caution

- This device is not intended for use with emergency exit fixtures or emergency lights.
- This lamp is not compatible with dimmers. During installation, ensure that the power is switched off prior to connecting or disconnecting the lamp from the fixture.
- No user serviceable parts inside. To avoid electrical shock, do not disassemble the product.
- **RISK OF BURN**--Disconnect power and allow fixture to cool before servicing.
- To prevent injury or property damage from falling lamp, only use in fixtures that can structurally support this lamp.
- The condition of the lamp holder can affect the life hours of a bulb. Inspect the lamp holder regularly for deterioration. If deterioration has occurred, replace the lamp holder immediately before continuing operation.
- To prevent injury or premature failure, use in enclosed fixtures with a minimum compartment dimension of 20.7in X 5.8in (524.4mm X 147mm)

Precaución

- Este dispositivo no está diseñado para su uso con dispositivos de salida de emergencia o luces de emergencia.
- Esta lámpara no es compatible con dimmers. Durante la instalación, asegúrese de que la alimentación esté apagada antes de conectar o desconectar la lámpara del accesorio.
- No hay partes reparables por el usuario en el interior. Para evitar descargas eléctricas, no desmonte el producto.
- **RIESGO DE QUEMADURAS:** desconecte la alimentación y permita que el accesorio se enfríe antes de realizar el mantenimiento.
- Para evitar lesiones o daños a la propiedad por la caída de la lámpara, solo úselo en accesorios que puedan soportar estructuralmente esta lámpara.
- La condición del portalámparas puede afectar las horas de vida de una bombilla. Inspeccione regularmente el portalámparas para ver si está deteriorado. Si se ha deteriorado, reemplace el portalámparas inmediatamente antes de continuar la operación.
- Para evitar lesiones o fallas prematuras, úselo en accesorios cerrados con una dimensión mínima del compartimiento de 20.7 pulgadas X 5.8 pulgadas (524.4 mm X 147 mm)

