

Ballast compatibility list

36200B LED9.5W/PLC/DM/3CCT/4P G24Q



Electronic ballasts

Ballast Brand	Ballast Model	Lamp Quantity	Volatge	Compatibility
DAMAR	20091D	1	120V	OK
		2	120V	OK
DAMAR	23350D	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S18-H1-LD	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S26-H1-LD	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S13-M1-BS-QS	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S18-M1-BS-QS	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S26-M1-BS-QS	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Philips-Advance	ICF-2S42-M2-LD	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK

This ballast compatibility list has been provided for guidance when selecting a ballast and lamp combination.

Lamps were tested for compatibility with the above listed ballast.

Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

* Subject to change without notice..

Ballast compatibility list

36200B LED9.5W/PLC/DM/3CCT/4P G24Q



Electronic ballasts

Ballast Brand	Ballast Model	Lamp Quantity	Volatge	Compatibility
Philips-Advance	IZT-2S26-M5-BS	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C213UNVBES	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C213UNVME	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C218UNVME	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C218UNVBE	1	120V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C2642UNVME	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Triad/Universal Lighting	C2642UNVBE	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Sylvania	QTP 1/2x13CF/UNV DM	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK

This ballast compatibility list has been provided for guidance when selecting a ballast and lamp combination.

Lamps were tested for compatibility with the above listed ballast.

Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

* Subject to change without notice..

Ballast compatibility list

36200B LED9.5W/PLC/DM/3CCT/4P G24Q



Electronic ballasts

Ballast Brand	Ballast Model	Lamp Quantity	Volatge	Compatibility
Sylvania	QTP 1/2x18CF/UNV DM	2	120V	OK
		2	277V	OK
Sylvania	QTP 2x26/32/42CF/UNV DM	2	120V	OK
Howard	EP2/13CF/MV/2	1	120V	OK
		1	277V	OK
		2	120V	OK
		2	277V	OK
Sola	E-724-U-226-M1-S	1	120V	-
Fulham	WH2-277-L	1	277V	OK
		2	277V	OK
Fulham	WH3-277-L	1	277V	OK
		2	277V	OK
Fulham	WH4-277-L	1	277V	OK
		2	277V	OK
Robertson	RED1L10-120H	1	120V	OK

Magnetic ballasts

Ballast Brand	Model	120V		277V	
		Compatibility 1-lamp	Compatibility 2-lamp	Compatibility 1-lamp	Compatibility 2-lamp
Philips	H-1Q26-TP-BLS	OK	N/A	N/A	N/A
Robertson	HP28P	OK	N/A	N/A	N/A
Roberston	HP22627P	N/A	N/A	N/A	OK
Roberston	O1527P(3P10104)	N/A	N/A	OK	N/A

Emergency ballasts/drivers

Type A mode - EM BALLAST	
Ballast Brand	MODEL
Bodline	B30ST
Bodline	LP600
Iota	I-320
Fulham	FH5-DUAL-1400L
Lithonia	PS1400QD

Type B mode - EM DRIVER	
Driver Brand	MODEL
Fulham	FHSCP-UNV-10.7WL
Fulham	FHSCP-UNV-13.7WL
Fulham	FHSCP-UNV-17WL
GREEN CREATIVE	23EMDRIVER
GREEN CREATIVE	5EMDRIVER
GREEN CREATIVE	10EMDRIVER

This ballast compatibility list has been provided for guidance when selecting a ballast and lamp combination.

Lamps were tested for compatibility with the above listed ballast.

Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

* Subject to change without notice..

Ballast compatibility list

36200B LED9.5W/PLC/DM/3CCT/4P G24Q



Electronic ballasts

Ballast		Dimmer	0-10V Dimmer Compatibility				
			Lutron- Nova		Lutron- Diva		Leviton- Illumatech
			NTSTV- DV	NFTV	DVSCTV	DVSTV	IP710- LFZ
			960W	2000W	1000W	960W	1200W
Philips	IZT- 2S26- M5- BS	1- lamp	✓	✓	✓	✓	✓
		2- lamp	✓	✓	✓	✓	✓
Philips	IZT- 2S26- M5- LD	1- lamp	✓	✓	✓	✓	✓
		2- lamp	✓	✓	✓	✓	✓
Philips	IZT- 2T42- M5- BS	1- lamp	-	✓	✓	✓	-
		2- lamp	-	✓	✓	✓	-
Philips	IZT- 2T42- M5- LD	1- lamp	-	✓	✓	✓	-
		2- lamp	-	✓	✓	✓	-
Sylvania	QTP 2x26CF/UNV DIM	1- lamp	-	-	-	-	-
		2- lamp	✓	✓	✓	✓	✓

This ballast compatibility list has been provided for guidance when selecting a ballast and lamp combination.

Lamps were tested for compatibility with the above listed ballast.

Emergency ballasts that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above ballasts may affect lamp performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

* Subject to change without notice..